NCE N-Channel Enhancement Mode Power MOSFET

Description

The NCE75H21 uses advanced trench technology and design to provide excellent R_{DS(ON)} with low gate charge. It can be used in Automotive applications and a wide variety of other applications.

General Features


- V_{DSS} =75V,I_D =210A $R_{DS(ON)} < 4m\Omega @ V_{GS} = 10V$
- Good stability and uniformity with high E_{AS}
- Special process technology for high ESD capability
- High density cell design for ultra low Rdson
- Fully characterized avalanche voltage and current
- Excellent package for good heat dissipation

Application

- Automotive applications
- Hard switched and high frequency circuits
- Uninterruptible power supply

100% UIS TESTED!

100% ΔVds TESTED!



Schematic diagram



Marking and pin assignment



Package Marking and Ordering Information

Device Marking	evice Marking Device		Reel Size	Tape width	Quantity
NCE75H21	NCE75H21	TO-220	-	-	-

Absolute Maximum Ratings (TC=25℃unless otherwise noted)

Parameter	Symbol	Limit	Unit
Drain-Source Voltage	VDSS	75	V
Gate-Source Voltage	V _{GS}	±20	V
Drain Current-Continuous	I _D	210	А
Drain Current-Continuous(T _C =100°C)	I _D (100℃)	150	Α
Pulsed Drain Current	I _{DM}	840	Α
Maximum Power Dissipation	P _D	310	W
Derating factor		2.07	W/℃



http://www.ncepower.com

NCE75H21

Single pulse avalanche energy (Note 4)	E _{AS}	2200	mJ
Operating Junction and Storage Temperature Range	T_J, T_STG	-55 To 175	$^{\circ}$

Thermal Characteristic

Thermal Resistance, Junction-to-Case (Note 1)	R _{θJC}	0.48	°C/W
---	------------------	------	------

Electrical Characteristics (T_C=25°C unless otherwise noted)


Parameter		Symbol	Condition	Min	Тур	Max	Unit
Off Characteristics				•			
Drain-Source Breakdown Voltage		BV _{DSS}	V _{GS} =0V I _D =250μA	75			V
Zero Gate Voltage Drain Current		I _{DSS}	V _{DS} =75V,V _{GS} =0V			1	μA
Gate-Body Leakage Current		I _{GSS}	V _{GS} =±20V,V _{DS} =0V			±200	nA
On Characteristics							
Gate Threshold Voltage		$V_{GS(th)}$	$V_{DS}=V_{GS}$, $I_{D}=250\mu A$	2	3	4	V
Drain-Source On-State Resistance	25 ℃	В	V _{GS} =10V, I _D =40A		2.8	4	mΩ
Diain-Source On-State Resistance	125 ℃	R _{DS(ON)}			4.7	6.5	mΩ
Forward Transconductance		g FS	V _{DS} =25V,I _D =40A	100	165		S
Dynamic Characteristics							
Input Capacitance		C _{lss}	\/ -25\/\/ -0\/		11000		PF
Output Capacitance		C _{oss}	V_{DS} =25V, V_{GS} =0V, F=1.0MHz		914		PF
Reverse Transfer Capacitance		C _{rss}	r-1.0ivinz		695		PF
Switching Characteristics							
Turn-on Delay Time		t _{d(on)}			23		nS
Turn-on Rise Time		t _r	V_{DD} =30V, I_D =2A, R_L =15 Ω		190		nS
Turn-Off Delay Time		t _{d(off)}	V_{GS} =10V, R_{G} =2.5 Ω		130		nS
Turn-Off Fall Time		t _f			120		nS
Total Gate Charge		Qg		-	250		nC
Gate-Source Charge		Q _{gs}	ID=30A,VDD=30V,VGS=10V	-	48		nC
Gate-Drain Charge		Q_{gd}		-	98		nC
Drain-Source Diode Characteristic	s						
Diode Forward Voltage		V _{SD}	V _{GS} =0V,I _S =40A			1.2	V
Reverse Recovery Time		t _{rr}	TJ = 25°C, IF = 40A		63		nS
Reverse Recovery Charge		Qrr	di/dt = 100A/μs ^(Note2)		98		nC
Forward Turn-On Time	t _{on}	Intrinsic turn-on time is negligible (turn-on is dominated by LS+LD)					

Notes:


- **1.** Surface Mounted on FR4 Board, $t \le 10$ sec.
- 2. Pulse Test: Pulse Width ≤ 400µs, Duty Cycle ≤ 2%.
- 3. EAS condition: Tj=25°C,VDD=37.5V,VG=10V,L=2mH,Rg=25 Ω ,IAS=37A

Test circuit


1) E_{AS} test Circuit



2) Gate charge test Circuit



3) Switch Time Test Circuit



Typical Electrical and Thermal Characteristics




Figure 1 Output Characteristics




Figure 2 Transfer Characteristics




Figure 3 Rdson- Drain Current




Figure 4 Rdson-JunctionTemperature




Figure 5 Gate Charge




Figure 6 Source- Drain Diode Forward






Figure 7 Capacitance vs Vds




Figure 9 BV_{DSS} vs Junction Temperature




Figure 8 Safe Operation Area




Figure 10 V_{GS(th)} vs Junction Temperature





Figure 11 Normalized Maximum Transient Thermal Impedance

TO-220-3L Package Information



Cumbal	Dimensions	In Millimeters	Dimensions In Inches		
Symbol	Min.	Max.	Min.	Max.	
А	4.400	4.600	0.173	0.181	
A1	2.250	2.550	0.089	0.100	
b	0.710	0.910	0.028	0.036	
b1	1.170	1.370	0.046	0.054	
С	0.330	0.650	0.013	0.026	
c1	1.200	1.400	0.047	0.055	
D	9.910	10.250	0.390	0.404	
Е	8.9500	9.750	0.352	0.384	
E1	12.650	12.950	0.498	0.510	
е	2.540	TYP.	0.100 TYP.		
e1	4.980	5.180	0.196	0.204	
F	2.650	2.950	0.104	0.116	
Н	7.900	8.100	0.311	0.319	
h	0.000	0.300	0.000	0.012	
L	12.900	13.400	0.508	0.528	
L1	2.850	3.250	0.112	0.128	
V	7.500 REF.		0.295 REF.		
Ф	3.400	3.800	0.134	0.150	

NCE75H21

Attention:

- Any and all NCE power products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your NCE power representative nearest you before using any NCE power products described or contained herein in such applications.
- NCE power assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all NCE power products described or contained herein.
- Specifications of any and all NCE power products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- NCE power Semiconductor CO.,LTD. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all NCE power products(including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of NCE power Semiconductor CO.,LTD.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. NCE power believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the NCE power product that you intend to use.
- This catalog provides information as of Sep.2010. Specifications and information herein are subject to change without notice.